

DIR9001 Evaluation Board

Contents

1	Description	1
1.1	Block Diagram	2
1.2	Operation and Setting	2
2	Schematic, Printed-Circuit Board and Bill of Materials	5
2.1	DEM-DIR9001 Printed-Circuit Board	5
2.2	DEM-DIR9001 Schematic Circuit Diagram	7
2.3	Bill of Materials	8

List of Figures

1	DEM-DIR9001 Block Diagram	2
2	DEM-DIR9001 Silkscreen	5
3	DEM-DIR9001 — Top View	5
4	DEM-DIR9001 — Bottom View	6
5	Schematic	7

List of Tables

1	SW002: FMT0, FMT1 PCM Audio Data Format Selection	3
2	SW002: PSCK0, PSCK1 System Clock Frequency Selection	3

1 Description

The DEM-DIR9001 is an evaluation board for the low jitter, Digital Audio Interface Receiver DIR9001. It is operated by either a single +3.3 V power supply, or a +5 V power supply.

The DEM-DIR9001 has both an Optical Toslink input and an Coaxial input for the SPDIF interface which can achieve standard digital audio interface format IEC60958, AES/EBU, and JEIAT CPR-1205 (former EIAJ CP-1201, 340).

The DEM-DIR9001 recovers standard system clock and PCM audio interface clock from incoming biphasic signals such as SPDIF, IEC60958, and AES/EBU. These signals are provided to the audio DAC/DSP, buffer output, and direct output.

1.1 Block Diagram




Figure 1. DEM-DIR9001 Block Diagram

1.2 Operation and Setting

1.2.1 Power Supply

+5 V Power supply

Connect the +5 V power supply at CN051 with the 5V jumper connection at the HDR051 connector. For all internal operations, the +3.3 V power supply is generated by the mounted REG-IC. External +3.3 V is not required.

+3.3 V Power supply

Connect +3.3 V power supply at CN052 with 3.3 V jumper connection at the HDR051 connector. All +3.3 V power supply is provided from CN052.

1.2.2 Reset

SW001 is a reset switch for the DIR9001. External automatic power on the reset circuit is combined.

1.2.3 SPDIF Input and Selection

- Connect the Toslink optical fiber cable connector at U001.
- Connect the RCA Coaxial cable connector at CN001.
- Optical input or Coaxial input must be selected by SW003 as OPT or COAX.

1.2.4 Function Control

Table 1. SW002: FMT0, FMT1 PCM Audio Data Format Selection

FMT[1:0] SETTING		DOUT SERIAL AUDIO DATA OUTPUT FORMAT
FMT1	FMT0	
L	L	16-bit MSB first, right justified
L	H	24-bit MSB first, right justified
H	L	24-bit MSB first, left justified
H	H	24-bit MSB first, I ² S

Table 2. SW002: PSCK0, PSCK1 System Clock Frequency Selection

PSCK[1:0] SETTING		OUTPUT CLOCK AT PLL SOURCE		
PSCK1	PSCK0	SCKO	BCKO	LRCKO
L	L	128fs	64fs	fs
L	H	256fs	64fs	fs
H	L	384fs	64fs	fs
H	H	512fs	64fs	fs

1.2.5 Operation Mode Control

SW004 is the fundamental operation mode control for DIR9001.

XTAL: Outputs connected at the XTAL resonator clock and divided clock

AUTO: Outputs from either the PLL generated clock or the XTAL clock are automatically selected by the operation status of DIR9001.

DIR9001 is locked into SPDIF interface clock → PLL clock

DIR9001 is unlocked into SPDIF interface clock → XTAL clock

PLL: Outputs from the PLL generated clock

If in the PLL mode operation, XTAL clock is not required for all operations of the DIR9001.

1.2.6 CN003 Status Output

CN003 is the output for the Channel status (COUT), User bit (UOUT), Bit frame (BFRAME), and clock transition status (CLKST).

1.2.7 Status Indicator

The following status is shown with an LED indicator.

- ERROR : Unlock or Data parity error
- AUDIO : non audio data
- EMPH : with pre-emphasis
- FSOUT1 : detected sampling rate
- FSOUT2 : detected sampling rate


Description

1.2.8 CN004, CN005 PCM Audio Interface Clock Output

CN004 and CN005 are PCM audio interface clock outputs (System Clock, LRCK, BCK, and DATA). CN004 is a buffered output with a mounted logic buffer IC. CN005 is a direct output from DIR9001.

Caution: Pins on the right side are GND.

- SCKO : System Clock (128/256/384/512fs)
- BCKO : PCM audio, BCK clock (64fs)
- LRCKO : PCM audio, LRCK clock (fs)
- DOUT : PCM audio, DATA clock



1.2.9 External Clock Input

The external clock can be connected at CN002 (not mounted) by removing the mounted XTAL. This allows the user to confirm operation of the DIR9001 by another clock source.

2 Schematic, Printed-Circuit Board and Bill of Materials

This section presents the DEM-DIR9001 printed-circuit boards, the DEM-DIR9001 schematic, and the bill of materials.

2.1 DEM-DIR9001 Printed-Circuit Board




Figure 2. DEM-DIR9001 Silkscreen




Figure 3. DEM-DIR9001 — Top View




Figure 4. DEM-DIR9001 — Bottom View

2.2 DEM-DIR9001 Schematic Circuit Diagram




Figure 5. Schematic

2.3 Bill of Materials

Reference		Description	MFG.	Model	Value
Type	NO.				
C	1,3,4	Chip Ceramic Capacitor	Murata	GRM188B11E104KA01	0.1 μ F, K, 25 V
C	2,6,11	OS Capacitor	SANYO	16SS10M	10 μ F, M, 16 V
C	5	AL EL Capacitor	ELNA	RC3-16V100M	10 μ F, M, 16 V
C	7	Chip Ceramic Capacitor	Murata	GRM188B11E104KA01	0.1 μ F, K, 25 V
C	8,9	Ceramic Capacitor	Murata	RPE2C1H180J2P1Z01	18 pF, J, 50 V
C	10,14,15	Chip Ceramic Capacitor	Murata	GRM188B11E104KA01	0.1 μ F, K, 25 V
C	12	Polypropylene Capacitor	NISSEI	APSF0100J472	0.0047 μ F, J
C	13	Polypropylene Capacitor	NISSEI	APSF0100J683	0.068 μ F, J
C	51,52	OS Capacitor	SANYO	16SS10M	10 μ F, M, 16V
C	53	Chip Ceramic Capacitor	Murata	GRM188B11E104KA01	0.1 μ F, K, 25V
C	54	OS Capacitor	SANYO	16SS10M	10 μ F, M, 16V
CN	1	Pin Jack	SMK	LPR6520-0804	RCA PJ
CN	3	Header Pin	Honda Tsushin	FFC-5AMEP1	5 pin
CN	4,5	Header Pin	Honda Tsushin	FFC-8BMEP1	8 pin
CN	6	Connector	Honda Tsushin	Z-282-8FD	8 pin
CN	51,52	Terminal	Osada	OS-33	2 pin
CN	53	Header Pin	Honda Tsushin	FFC-3BMEP1	3 pin
D	1	Diode	ROHM	1SS133	
D	2	LED	TOSHIBA	TLGU53D	Green
D	3,4	LED	TOSHIBA	TLOU124	Orange
D	5	LED	TOSHIBA	TLSU124	Red
D	6	LED	TOSHIBA	TLYU124	Yellow
R	1	1/4W Resistor	KOA	MFS1/4CC750RF	75 Ω , F, 1/4 W
R	2	1/4W Resistor	KOA	MFS1/4CC470RF	47 Ω , F, 1/4 W
R	3	1/4W Resistor	KOA	MFS1/4CC2201F	2.2 k Ω , F, 1/4 W
R	4,5	1/4W Resistor	KOA	MFS1/4CC470RF	47 Ω , F, 1/4 W
R	8	1/4W Resistor	KOA	MFS1/4CC6800F	680 Ω , F, 1/4 W
R	9-20	1/4W Resistor	KOA	MFS1/4CC330RF	33 Ω , F, 1/4 W
R	21	1/4W Resistor	KOA	MFS1/4CC2201F	2.2 k Ω , F, 1/4 W
R	22	1/4W Resistor	KOA	MFS1/4CC4700F	470 Ω , F, 1/4 W
R	23	1/4W Resistor	KOA	MFS1/4CC6800F	680 Ω , F, 1/4 W
R	24,25	1/4W Resistor	KOA	MFS1/4CC1501F	1.5 k Ω , F, 1/4 W
R	51	1/4W Resistor	KOA	MFS1/4CC2202F	22 k Ω , F, 1/4 W
SW	1	Tact Switch	ALPS	SKHRAAA010	
SW	2	DIP Switch	Fujisoku	DSS104	
SW	3	Toglle Switch	Fujisoku	FT1D-2M	
SW	4	Toglle Switch	Fujisoku	FT1E-2M	
TP	1	Test Pin	Mac 8	LC-2-G	Green
TP	2,3	Test Pin	Mac 8	LC-2-G	Orange
TP	4	Test Pin	Mac 8	LC-2-G	Red
TP	5	Test Pin	Mac 8	LC-2-G	Yellow
U	1	TOSLINK	TOSHIBA	TORX141P	
U	2	Logic IC	TI	SN74LVU04ANSR	
U	3	DIR	TI	PCM9001PW	
U	4	Regulator	TI	REG1117-3.3	800 mA, 3.3 V
U	5	Logic IC	TI	SN74LV541APW	
U	6	Logic IC	TI	SN74LV541APW	
X	1	Crystal Resonator	Kinseki	HC-49/U-S	24.576 MHz

EVALUATION BOARD/KIT IMPORTANT NOTICE

Texas Instruments (TI) provides the enclosed product(s) under the following conditions:

This evaluation board/kit is intended for use for **ENGINEERING DEVELOPMENT, DEMONSTRATION, OR EVALUATION PURPOSES ONLY** and is not considered by TI to be a finished end-product fit for general consumer use. Persons handling the product(s) must have electronics training and observe good engineering practice standards. As such, the goods being provided are not intended to be complete in terms of required design-, marketing-, and/or manufacturing-related protective considerations, including product safety and environmental measures typically found in end products that incorporate such semiconductor components or circuit boards. This evaluation board/kit does not fall within the scope of the European Union directives regarding electromagnetic compatibility, restricted substances (RoHS), recycling (WEEE), FCC, CE or UL, and therefore may not meet the technical requirements of these directives or other related directives.

Should this evaluation board/kit not meet the specifications indicated in the User's Guide, the board/kit may be returned within 30 days from the date of delivery for a full refund. **THE FOREGOING WARRANTY IS THE EXCLUSIVE WARRANTY MADE BY SELLER TO BUYER AND IS IN LIEU OF ALL OTHER WARRANTIES, EXPRESSED, IMPLIED, OR STATUTORY, INCLUDING ANY WARRANTY OF MERCHANTABILITY OR FITNESS FOR ANY PARTICULAR PURPOSE.**

The user assumes all responsibility and liability for proper and safe handling of the goods. Further, the user indemnifies TI from all claims arising from the handling or use of the goods. Due to the open construction of the product, it is the user's responsibility to take any and all appropriate precautions with regard to electrostatic discharge.

EXCEPT TO THE EXTENT OF THE INDEMNITY SET FORTH ABOVE, NEITHER PARTY SHALL BE LIABLE TO THE OTHER FOR ANY INDIRECT, SPECIAL, INCIDENTAL, OR CONSEQUENTIAL DAMAGES.

TI currently deals with a variety of customers for products, and therefore our arrangement with the user **is not exclusive.**

TI assumes **no liability for applications assistance, customer product design, software performance, or infringement of patents or services described herein.**

Please read the User's Guide and, specifically, the Warnings and Restrictions notice in the User's Guide prior to handling the product. This notice contains important safety information about temperatures and voltages. For additional information on TI's environmental and/or safety programs, please contact the TI application engineer or visit www.ti.com/esh.

No license is granted under any patent right or other intellectual property right of TI covering or relating to any machine, process, or combination in which such TI products or services might be or are used.

FCC Warning

This evaluation board/kit is intended for use for **ENGINEERING DEVELOPMENT, DEMONSTRATION, OR EVALUATION PURPOSES ONLY** and is not considered by TI to be a finished end-product fit for general consumer use. It generates, uses, and can radiate radio frequency energy and has not been tested for compliance with the limits of computing devices pursuant to part 15 of FCC rules, which are designed to provide reasonable protection against radio frequency interference. Operation of this equipment in other environments may cause interference with radio communications, in which case the user at his own expense will be required to take whatever measures may be required to correct this interference.

Mailing Address: Texas Instruments, Post Office Box 655303, Dallas, Texas 75265
Copyright © 2007, Texas Instruments Incorporated

EVM WARNINGS AND RESTRICTIONS

It is important to operate this EVM within the input voltage range of 2.7 V to 3.6 V or 5 V and the output voltage range of 2.7 V to 3.6 V.

Exceeding the specified input range may cause unexpected operation and/or irreversible damage to the EVM. If there are questions concerning the input range, please contact a TI field representative prior to connecting the input power.

Applying loads outside of the specified output range may result in unintended operation and/or possible permanent damage to the EVM. Please consult the EVM User's Guide prior to connecting any load to the EVM output. If there is uncertainty as to the load specification, please contact a TI field representative.

During normal operation, some circuit components may have case temperatures greater than 85°C. The EVM is designed to operate properly with certain components above 85°C as long as the input and output ranges are maintained. These components include but are not limited to linear regulators, switching transistors, pass transistors, and current sense resistors. These types of devices can be identified using the EVM schematic located in the EVM User's Guide. When placing measurement probes near these devices during operation, please be aware that these devices may be very warm to the touch.

Mailing Address: Texas Instruments, Post Office Box 655303, Dallas, Texas 75265
Copyright © 2007, Texas Instruments Incorporated

IMPORTANT NOTICE

Texas Instruments Incorporated and its subsidiaries (TI) reserve the right to make corrections, modifications, enhancements, improvements, and other changes to its products and services at any time and to discontinue any product or service without notice. Customers should obtain the latest relevant information before placing orders and should verify that such information is current and complete. All products are sold subject to TI's terms and conditions of sale supplied at the time of order acknowledgment.

TI warrants performance of its hardware products to the specifications applicable at the time of sale in accordance with TI's standard warranty. Testing and other quality control techniques are used to the extent TI deems necessary to support this warranty. Except where mandated by government requirements, testing of all parameters of each product is not necessarily performed.

TI assumes no liability for applications assistance or customer product design. Customers are responsible for their products and applications using TI components. To minimize the risks associated with customer products and applications, customers should provide adequate design and operating safeguards.

TI does not warrant or represent that any license, either express or implied, is granted under any TI patent right, copyright, mask work right, or other TI intellectual property right relating to any combination, machine, or process in which TI products or services are used. Information published by TI regarding third-party products or services does not constitute a license from TI to use such products or services or a warranty or endorsement thereof. Use of such information may require a license from a third party under the patents or other intellectual property of the third party, or a license from TI under the patents or other intellectual property of TI.

Reproduction of TI information in TI data books or data sheets is permissible only if reproduction is without alteration and is accompanied by all associated warranties, conditions, limitations, and notices. Reproduction of this information with alteration is an unfair and deceptive business practice. TI is not responsible or liable for such altered documentation. Information of third parties may be subject to additional restrictions.

Resale of TI products or services with statements different from or beyond the parameters stated by TI for that product or service voids all express and any implied warranties for the associated TI product or service and is an unfair and deceptive business practice. TI is not responsible or liable for any such statements.

TI products are not authorized for use in safety-critical applications (such as life support) where a failure of the TI product would reasonably be expected to cause severe personal injury or death, unless officers of the parties have executed an agreement specifically governing such use. Buyers represent that they have all necessary expertise in the safety and regulatory ramifications of their applications, and acknowledge and agree that they are solely responsible for all legal, regulatory and safety-related requirements concerning their products and any use of TI products in such safety-critical applications, notwithstanding any applications-related information or support that may be provided by TI. Further, Buyers must fully indemnify TI and its representatives against any damages arising out of the use of TI products in such safety-critical applications.

TI products are neither designed nor intended for use in military/aerospace applications or environments unless the TI products are specifically designated by TI as military-grade or "enhanced plastic." Only products designated by TI as military-grade meet military specifications. Buyers acknowledge and agree that any such use of TI products which TI has not designated as military-grade is solely at the Buyer's risk, and that they are solely responsible for compliance with all legal and regulatory requirements in connection with such use.

TI products are neither designed nor intended for use in automotive applications or environments unless the specific TI products are designated by TI as compliant with ISO/TS 16949 requirements. Buyers acknowledge and agree that, if they use any non-designated products in automotive applications, TI will not be responsible for any failure to meet such requirements.

Following are URLs where you can obtain information on other Texas Instruments products and application solutions:

Products		Applications	
Amplifiers	amplifier.ti.com	Audio	www.ti.com/audio
Data Converters	dataconverter.ti.com	Automotive	www.ti.com/automotive
DSP	dsp.ti.com	Broadband	www.ti.com/broadband
Interface	interface.ti.com	Digital Control	www.ti.com/digitalcontrol
Logic	logic.ti.com	Military	www.ti.com/military
Power Mgmt	power.ti.com	Optical Networking	www.ti.com/opticalnetwork
Microcontrollers	microcontroller.ti.com	Security	www.ti.com/security
RFID	www.ti-rfid.com	Telephony	www.ti.com/telephony
Low Power Wireless	www.ti.com/lpw	Video & Imaging	www.ti.com/video
		Wireless	www.ti.com/wireless

Mailing Address: Texas Instruments, Post Office Box 655303, Dallas, Texas 75265
Copyright © 2007, Texas Instruments Incorporated