



SW-HF5.1 5000

5.1 Home Theater Speaker System

Music Makes Your Life Better

If good music and movies really matter in your life, then the Genius new six-piece all wood home theater speaker system, SW-HF5.1 5000, will make your life better. It's designed to work with your music, DVD movies and gaming and can fill your home with great surround sound.

SW-HF5.1 5000 provides incredible good sound and more power. It features an extremely high power 150W RMS, the 6.5" long-throw subwoofer provides 75 watts, and deep rich bass tones from all the speakers. The center, front and surround speakers are two-way with 15W RMS maximum power handling per channel. The subwoofer includes RCA inputs and one 9-pin din connector for connecting with a DVD player, Game console, MP3 player, CD player or PC sound card.

The full feature remote control lets you sit back and you can adjust the master volume, stand by, mute and select the input (four).

Two optional finishes are available: Dark Brown and Light Wood

Contact with your sales representatives for more information.



Color: Dark Brown



Color: Light Wood

Features:

- Six-piece all wood home theater speaker system with a total of 150 watts RMS output power
 - Subwoofer: 75 watts
 - Center/Front/Surround speakers: 15 watts per channel
- Create 5.1 surround sound for music, movies and video games
- Great for working with DVD player, Game console and MP3/CD players
- Remote control include:
 - Stand by and mute
 - Master volume
 - 4 audio sources

Dates Available

- ◆ Sample: Dec, 2005
- ◆ Delivery: Jan, 2006

Front Panel Controls



Master volume control adjusts automatically when you turn up/down the volume on the remote control.

Back Connectivity



SW-HF5.1 5000

5.1 Home Theater Speaker System

Applications:



Specifications:

Output power	150 watts RMS Subwoofer: 75 watts Satellites & Center: 15 watts each at THD10%	
Drivers	<ul style="list-style-type: none"> Subwoofer: 6.5" Woofer Front Speaker: 4" Full Range and 1" Dome Tweeter Rear Speaker: 3" Full Range and 1" Dome Tweeter Center Speaker: 4" Full Range and 1" Dome Tweeter x 2 	
Impedance	<ul style="list-style-type: none"> Woofer: 4 Ohms Satellites & Center: 4 Ohms 	
Fuse	<ul style="list-style-type: none"> AC 250V/2A (Local Voltage: 220 ~ 240V) AC 125V/2A (Local Voltage: 100 ~ 120V) 	
AC IN	AC transformer built-in	
Frequency Response	40Hz ~ 20KHz	
Signal-to-Noise Ratio (SNR)	85 dB@	
Audio Input	<ul style="list-style-type: none"> Six RCA Audio Input Jacks for 5.1 Channel DVD player. Three pairs of RCA jacks for two-channel DVD players, TV, PC, CD players, MP3 players and game consoles. 	
IR Receiver	Built-in in Subwoofer	
Amplifier	Built-in in Subwoofer	
WEEE DATA	Dimensions (W x H x D)	<ul style="list-style-type: none"> Subwoofer: 220 x 412 x 344 mm Center Speaker: 332 x 142 x 155 mm Front Speaker: 140 x 217 x 165 mm (each) Satellite Speaker: 120 x 197 x 140 mm (each)
	Remote Control	<ul style="list-style-type: none"> Battery: 2025 3V x 1
	Speaker body weight (g)	19,000g
	Size of gift box (W x H x D)	658 x 468 x 386 mm
PCS/Carton	1 set / 1 carton	
Loading measurement	4.20 cu.ft.	
20'CY / 40'CY / 40HQ	255 / 540 / 540 sets	



Package contents:

- One subwoofer speaker
- One instruction manual
- One center speaker
- One 6 RCA to 6 RCA cable
- Two front speakers
- One 3.5mm to dual RCA cable
- Two surround speakers
- One G9 to 3x3.5mm cable
- One remote control
- Five bare wires



SW-HF5.1 5000

5.1 Home Theater Speaker System

Comparison List :		
Model Name	SW-5.1HT	SW-HF5.1 5000
Image		
Specifications		
Total RMS (Watt)	120	150
Woofer	45	75
Center	15	15
Front	15*2	15*2
Rear	15*2	15*2
Driver		
Woofer	6.5" woofer	6.5" woofer
Center	2 x 4" full-range + tweeter	2 x 4" full-range + tweeter
Front	4" full-range + tweeter	4" full-range + tweeter
Rear	3" full-range	3" full-range + tweeter
Frequency Response	20 ~ 20K Hz	20~20K Hz
Signal-to-Noise ratio	80dB	85dB
Function		
Master Volume	Y	Y
Center Volume	Y	Y
Surround Volume	Y	Y
Woofer Volume	Y	Y
Mute	Y	Y
Bass	Y	Y
Aux Input	3	3
Power Source	AC transformer built-in	AC transformer built-in
Color Available	Beech Wood (light wood)	Beech Wood (light wood) and Pear Wood (dark brown)
Front Panel Controls		
Stand-By button	Y	Y
Master Volume Switch	Y	Y
Center/Woofer/Surround Switches	Y	Y
Input Source Selection buttons	AC-2, TV, TAPE and CD/VCD/DVD (2CH)	DVD, TV, GAME and CD/MP3
Mute button	Y	Y
Front Panel LED colors	Green lights and red for Mute	Blue lights and red for Mute
IR Controls		
Stand-By	Y	Y
Master Volume up/down	Y	Y
Mute	Y	Y
Input Source Selection	N	Y
Connectivity on the back subwoofer		
Six-channel Input 1(Six RCA jacks)	Y	Y
Six-channel Input 2 (9-pin Din jack)	Y	Y
Three two-channel Input (RCA jacks)	Y	Y
Power on/off switch	Y	Y
Output (Spring Tags)	Y	Y
Enclosing cables		
Bare wires	5pcs	5pcs
RCA to RCA cable	6 x RCA to RAC cables	1 x 6RCA to 6RCA cable
G9 Din to 3x3.5mm cable for sound card	Y	Y
Converter cable for different Cen/Subwoofer sound card design	Y	Y
Two RCA to 3.5mm cable for connecting with two-channel audio source such as MP3, CD players, Game consoles	N	Y
Dimension (mm)		
Subwoofer	220x398x354	220x412x344
Center Speaker	360x160x165	332x142x155
Front Speaker (each)	160x235x165	140x217x165
Rear Speaker (each)	120x120x120	120x197x140
Packing		
PCS / Carton	1 pc	1pc
20°C/Y / 40°C/Y / 40HQ	228 / 468(450) / 516 sets	255 / 540 / 540 sets
Remark:	For those in red on the above list are better functions and designs the SW-HT5.1 5000 has than the SW-5.1 HT.	