

SPECIÁLIS 1 ÉS HÁROM FÁZISÚ VILLAMO

Főfázis											
sz.	Típus	telj. W	áram- felv. A	tek. rend- szer	kapcs. jele	tek. száma	t. láb sz.	lépés	menet szám	huzal Ø	ell. áll. ohm
7	GO 232 B702X 220V	5,3	0,27	pólus- tekercs	soros	2				1x 0,23	15
									890		
8	KU 752 F7n 220V	700 felvett	4,5	kon- cent- rikus	soros	2	1	1-12	44	1x 0,8	4,
							2	1-10	44		
							3	1-8	44		
							4	1-6	44		
9	HZ 762 R7h2 220V	400	3,6	kon- cent- rikus	soros	2	1	1-12	46	1x 0,8	4,
							2	1-10	46		
							3	1-8	46		
							4	1-6	46		
10	HZ 792 R7j 220V	750	6,8	kon- cent- rikus	soros	2	1	1-12	28	2x 0,75	2
							2	1-10	28		
							3	1-8	28		
							4	1-6	28		
11	HZ 792 R802 3 x 380	1500	3,3	kon- cent- rikus	soros	6				2x 0,55	7,
							1	1-12	50		
							2	1-10	50		
12	HZ 772 R7 e1 220V	750	4,8	kon- cent- rikus	soros	2	1	1-12	38	2x 0,65	3,
							2	1-10	38		
							3	1-8	38		
							4	1-6	38		
13	HZM 90L-4/199 380/220V	1500		félhor- nyos kon- cent- rikus	S/p	12	1	1-7	25	2x 0,6	3,
							2	1-9	25		
							3	1-11	25		
14	OZM 90L-4N/200 220V	750	6,7	sinusos kon- cent- rikus	soros	4	1	1-9	31	2x 0,75	2,
							2	1-7	29		
							3	1-5	20		
							4	1-3	11		