



NOTE ON PARTS :

BOARD	PART	IN SCHEMATIC	ON BOARD
P701	R801, R808	68 (2W)	47 (2W)
	R809	33 (1/4W)	220 (1/4W)
	C806	0.47/50V	4.7/50
PS01	C703, C704	Elco. polar	Elco. bipolar
	RS01, RS02	6.8k	5.6k
	RS03, RS04	6.8k	47k
	CS01, CS02	0.082uF	0,056uF
PE01	CS03, CS04	1000p	470p
	CE05, CE06	Elco. polar	Elco. bipolar

NOTE ON SAFETY :
 Symbol Fire or electrical shock hazard. Only original parts should be used to replace any part marked with symbol Any other component substitution (other than original type), may increase risk of fire or electrical shock hazard.

"SERVICE INFORMATION IS FOR USE BY QUALIFIED PERSONEL ONLY - ANY MISADJUSTMENT OR MISALIGNMENT MAY BE TREATED AS NON-WARRANTY REPAIR BY ANY MARANTZ SERVICE CENTRE."

Kind of Common Parts

RESISTOR	R*** (1) GD05 - - 140, Carbon film fixed resistor, ±5% 1/4W	C*** : ELECTROLY CAP. (≡) / FILM CAP. (≡)
	R*** (2) GD05 - - 140, Carbon film fixed resistor, ±5% 1/6W	(1) EA - - - 10, Electrolytic condenser, one-way lead type, tolerance ±20%
CERAMIC CAP.	C*** : CERAMIC CAP. (1) DD1 - - 370, Ceramic condenser, disc type (titan condenser) Temp. coeff. P350 ~ N1000 50V	(2) DF15 - - 350, Plastic film condenser, one-way type, Mylar, ±5% 50V
CERAMIC CAP.	C*** : CERAMIC CAP. (1) DK16 - - 300, High dielectric constant ceramic condenser, disc type (titan variable) Temp. chara. 2B4 50V	

In case of ordering the common parts, please establish the correct parts number of 10 figures by the procedure "ASSIGNMENT OF COMMON PARTS CODES"